

PPG1350P

Perkins diesel generator | Open set

Designed and manufactured in the United Kingdom

1350 kVA

ROUNDED CATALOGUE CLASS



SELECTED CONFIGURATION

ENGINE

Perkins 4012-46TWG2A

ALTERNATOR

Stamford S6L1D-G41

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Representative manufacturer image; final build may vary.

PRIME POWER / PRP

1250 kVA

1000 kW

STANDBY POWER / ESP

1345 kVA

1076 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
380	SS	1290	1032	1205	964
400	SS	1345	1076	1250	1000

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.



Technical specification

PPG1350P | Perkins 4012-46TWG2A | Open set

ENGINE

Manufacturer	Perkins
Model	4012-46TWG2A
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	12
Arrangement	At Vee
Displacement	45.84L
Bore	160mm
Stroke	190mm
Compression ratio	12.8:1
Cooling	Liquid Cooled
Coolant capacity	173L
Oil capacity	157.5L

ALTERNATOR

Manufacturer	Stamford
Model	S6L1D-G41
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	MX321
Voltage regulation	0.5%
Insulation class	H
Excitation	PMG
Winding	312
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 133 L/h	75% LOAD 191.6 L/h	100% LOAD 255.5 L/h	110% LOAD 284 L/h
----------------------------	------------------------------	-------------------------------	-----------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

L x W x H (mm) 4800 x 1920 x 2543	REFERENCE WEIGHT 9187.75 kg
---	---------------------------------------

Reference frame GenericPerkins4000 (Export). Drawing, weights and tank capacity are subject to the ordered build.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12