



PPG1550C

Cummins diesel generator | Open set

Designed and manufactured in the United Kingdom

1550 kVA

ROUNDED CATALOGUE CLASS

ENGINE PLATFORM

Cummins

QSK50G3

Model-specific drawing supplied with quotation.

SELECTED CONFIGURATION

ENGINE

Cummins QSK50G3

ALTERNATOR

Stamford S7L1D-C41

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Configuration and appearance are confirmed with the quotation.

PRIME POWER / PRP

1398 kVA

1118 kW

STANDBY POWER / ESP

1557 kVA

1246 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
380	SS	1555	1244	1397	1118
400	SS	1557	1246	1398	1118

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.



Technical specification

PPG1550C | Cummins QSK50G3 | Open set

ENGINE

Manufacturer	Cummins
Model	QSK50G3
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	16
Arrangement	At Vee
Displacement	50.3L
Bore	159mm
Stroke	159mm
Compression ratio	15.0:1
Cooling	Liquid Cooled
Coolant capacity	468.1L
Oil capacity	234.7L

ALTERNATOR

Manufacturer	Stamford
Model	S7L1D-C41
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	MX341
Voltage regulation	1%
Insulation class	H
Excitation	PMG
Winding	312
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 150 L/h	75% LOAD 217 L/h	100% LOAD 284 L/h	110% LOAD 323 L/h
-----------------------------------	-----------------------------------	------------------------------------	------------------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

Dimensions, weight, fuel tank and model-specific drawing are confirmed with the quotation.

No complete matching frame data is published for this selected configuration.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12