

PPG1850P

Perkins diesel generator | Open set

Designed and manufactured in the United Kingdom

1850 kVA

ROUNDED CATALOGUE CLASS



SELECTED CONFIGURATION

ENGINE

Perkins 4012-46TAG3A

ALTERNATOR

Stamford S7L1D-E41

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Representative manufacturer image; final build may vary.

PRIME POWER / PRP

1728 kVA

1382 kW

STANDBY POWER / ESP

1873 kVA

1498 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
380	SS	1819	1455	1700	1360
400	SS	1873	1498	1728	1382

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.



Technical specification

PPG1850P | Perkins 4012-46TAG3A | Open set

ENGINE

Manufacturer	Perkins
Model	4012-46TAG3A
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	12
Arrangement	At Vee
Displacement	45.84L
Bore	160mm
Stroke	190mm
Compression ratio	12.8:1
Cooling	Liquid Cooled
Coolant capacity	233L
Oil capacity	157.5L

ALTERNATOR

Manufacturer	Stamford
Model	S7L1D-E41
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	MX341
Voltage regulation	1%
Insulation class	H
Excitation	PMG
Winding	312
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 188.8 L/h	75% LOAD 280.5 L/h	100% LOAD 363.3 L/h	110% LOAD 401.3 L/h
-------------------------------------	-------------------------------------	--------------------------------------	--------------------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

L x W x H (mm) 4948 x 2164 x 2782	REFERENCE WEIGHT 10451.5 kg
--	--

Reference frame GenericPerkins4000 (Export). Drawing, weights and tank capacity are subject to the ordered build.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12