



PPG1900BS

Baudouin diesel generator | Acoustic canopied

Designed and manufactured in the United Kingdom

1900 kVA

ROUNDED CATALOGUE CLASS

ENGINE PLATFORM

Baudouin

16M33G1900/5

Model-specific drawing supplied with quotation.

SELECTED CONFIGURATION

ENGINE

Baudouin 16M33G1900/5

ALTERNATOR

Stamford S7L1D-F41

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Configuration and appearance are confirmed with the quotation.

PRIME POWER / PRP

1746 kVA

1397 kW

STANDBY POWER / ESP

1922 kVA

1538 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
380	SS	1922	1538	1745	1396
400	SS	1922	1538	1746	1397

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.

Technical specification

PPG1900BS | Baudouin 16M33G1900/5 | Acoustic canopied

ENGINE

Manufacturer	Baudouin
Model	16M33G1900/5
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	ECU
Cylinders	16
Arrangement	At Vee
Displacement	52.3L
Bore	150mm
Stroke	185mm
Compression ratio	15:1
Cooling	Liquid Cooled
Coolant capacity	400L
Oil capacity	175L

ALTERNATOR

Manufacturer	Stamford
Model	S7L1D-F41
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	MX341
Voltage regulation	1%
Insulation class	H
Excitation	PMG
Winding	312
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 179.7 L/h	75% LOAD 265.4 L/h	100% LOAD 364.3 L/h	110% LOAD 407.6 L/h
-------------------------------------	-------------------------------------	--------------------------------------	--------------------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

Dimensions, weight, fuel tank and model-specific drawing are confirmed with the quotation.

No complete matching frame data is published for this selected configuration.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12