



PPG2200PS

Perkins diesel generator | Acoustic canopied

Designed and manufactured in the United Kingdom

2200 kVA

ROUNDED CATALOGUE CLASS

ENGINE PLATFORM

Perkins

4016-61TRG2

Model-specific drawing supplied with quotation.

SELECTED CONFIGURATION

ENGINE

Perkins 4016-61TRG2

ALTERNATOR

Leroy Somer LSA52.3S6

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Configuration and appearance are confirmed with the quotation.

PRIME POWER / PRP

2000 kVA

1600 kW

STANDBY POWER / ESP

2200 kVA

1760 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
400	SS	2200	1760	2000	1600

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.



Technical specification

PPG2200PS | Perkins 4016-61TRG2 | Acoustic canopied

ENGINE

Manufacturer	Perkins
Model	4016-61TRG2
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	16
Arrangement	At Vee
Displacement	61.123L
Bore	160mm
Stroke	190mm
Compression ratio	13:1
Cooling	Liquid Cooled
Coolant capacity	300L
Oil capacity	213L

ALTERNATOR

Manufacturer	Leroy Somer
Model	LSA52.3S6
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	D550
Voltage regulation	0.5%
Insulation class	H
Excitation	Auxiliary Wound
Winding	6S
Harmonic content	<2.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 208 L/h	75% LOAD 306 L/h	100% LOAD 405 L/h	110% LOAD 463 L/h
-----------------------------------	-----------------------------------	------------------------------------	------------------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

Dimensions, weight, fuel tank and model-specific drawing are confirmed with the quotation.

No complete matching frame data is published for this selected configuration.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12