



PPG270P

Perkins diesel generator | Open set

Designed and manufactured in the United Kingdom

270 kVA

ROUNDED CATALOGUE CLASS

ENGINE PLATFORM

Perkins

1206A-E70TTAG3

Model-specific drawing supplied with quotation.

SELECTED CONFIGURATION

ENGINE

Perkins 1206A-E70TTAG3

ALTERNATOR

Leroy Somer TAL046D

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Configuration and appearance are confirmed with the quotation.

PRIME POWER / PRP

248 kVA

198 kW

STANDBY POWER / ESP

270 kVA

216 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
400	SS	270	216	248	198

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.



Technical specification

PPG270P | Perkins 1206A-E70TTAG3 | Open set

ENGINE

Manufacturer	Perkins
Model	1206A-E70TTAG3
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	6
Arrangement	In Line
Displacement	7.01L
Bore	105mm
Stroke	135mm
Compression ratio	15.8:1
Cooling	Liquid Cooled
Coolant capacity	25.0L
Oil capacity	16.0L

ALTERNATOR

Manufacturer	Leroy Somer
Model	TAL046D
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	6
AVR	R150
Voltage regulation	1%
Insulation class	H
Excitation	Self Excited
Winding	6S
Harmonic content	<5.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 28.1 L/h	75% LOAD 41.5 L/h	100% LOAD 56.9 L/h	110% LOAD 64.5 L/h
------------------------------------	------------------------------------	-------------------------------------	-------------------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

L x W x H (mm) 3000 x 1000 x 1767	REFERENCE WEIGHT 1825.6 kg	FUEL TANK 730 L
--	---	----------------------------------

Reference frame 9007GA (Export). Drawing, weights and tank capacity are subject to the ordered build.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12