

PPG350PS

Perkins diesel generator | Acoustic canopied

Designed and manufactured in the United Kingdom

350 kVA

ROUNDED CATALOGUE CLASS



SELECTED CONFIGURATION

ENGINE

Perkins 1506A-E88TAG5

ALTERNATOR

KWise C314G320

ELECTRICAL OUTPUT

400 V | 3-phase | 50 Hz

Representative PPG enclosure; final build may vary.

PRIME POWER / PRP

316 kVA

253 kW

STANDBY POWER / ESP

347 kVA

278 kW

Ratings shown at 400 V, 3-phase, 50 Hz. The PPG model number is a rounded class; use the exact ratings for selection.

PUBLISHED ELECTRICAL RATINGS

Voltage (V)	Connection	ESP (kVA)	ESP (kW)	PRP (kVA)	PRP (kW)
200	PS	347	278	316	253
230	SD	347	278	316	253
400	SS	347	278	316	253

PRP = prime power. ESP = emergency standby power. Values apply to the selected engine and alternator above. Connection codes follow the reference specification and must be confirmed before installation.



Technical specification

PPG350PS | Perkins 1506A-E88TAG5 | Acoustic canopied

ENGINE

Manufacturer	Perkins
Model	1506A-E88TAG5
Aspiration	Turbocharged
Combustion	Direct Injection
Cycle	4 Stroke
Governor	Electronic
Cylinders	6
Arrangement	In Line
Displacement	8.8L
Bore	112mm
Stroke	149mm
Compression ratio	16.1:1
Cooling	Liquid Cooled
Coolant capacity	33.2L
Oil capacity	41.0L

ALTERNATOR

Manufacturer	KWise
Model	C314G320
Type	Brushless
Phases	3
Bearings	1
Poles	4
Leads	12
AVR	SX440
Voltage regulation	1%
Insulation class	H
Excitation	PMG
Winding	311
Harmonic content	<3.00%
Short circuit	>300%

REFERENCE FUEL CONSUMPTION

50% LOAD 33 L/h	75% LOAD 48.2 L/h	100% LOAD 64.9 L/h	110% LOAD 73.1 L/h
----------------------------------	------------------------------------	-------------------------------------	-------------------------------------

Reference figures vary with operating conditions and the confirmed duty.

INSTALLATION INFORMATION

L x W x H (mm) 3958 x 1504 x 2384	REFERENCE WEIGHT 3593.65 kg	FUEL TANK 500 L
--	--	----------------------------------

Reference frame 2900E (UK/EU). Drawing, weights and tank capacity are subject to the ordered build.

SPECIFY YOUR PROJECT

Tell us your site load, required voltage and phase, prime or standby duty, ambient conditions and installation requirements. PPG will confirm a suitable build and its exact specification.

Final enclosure, controls, protection, acoustics and emissions suitability must be specified for the project. This sheet is a configuration guide, not an installation drawing.

PPG technical specification | Reviewed 2026-10-12